

振动棒产品系列

型号 TYPE	棒径 Ø NEEDLE (mm)	棒体长度 NEEDLE LENGTH (mm)	转速 v.p.m.	激振力 Fc (kg)	电流 A	重量 WEIGHT (kg)
VAF36	36	350	12,000	106	6	8
VAF36-1	36	370	12,000	230	7	8
VAF50	50	360	12,000	275	8	12
VAF50-1	57	442	12,000	572	18	16
VAF60	60	365	12,000	442	12	12
VAF60-1	65	460	12,000	650	21	18
VAF85-1	85	1200	12,000	750	30	21

Standard equipment: 6 metre rubber hose – 10 metre cable – ABS switch box
VAF85-1 without rubber hose, 2 metre cable

标准配置: 6M橡胶管, 10M电缆线, ABS开关盒

VAF85-1采用点联式, 无橡胶管, 2M电缆线

插入式振动棒 IMMERSION VIBRATORS



VAF36 - VAF60-1




VAF85-1

变频器 FREQUENCY CONVERTERS



CP



CM2M CM2T



CM1M



CM3T CM5T

型号 TYPE	输入电源 INPUT VOLTAGE	输出电源 OUTPUT VOLTAGE	输出功率 POWER (KVA)	输出电流 INTENSITY (A)	插座数 SOCKETS	重量 WEIGHT (kg)
CP1M	220 V / 50 Hz	42 V / 200 Hz	0.8	11	1	18
CP2M	220 V / 50 Hz	42 V / 200 Hz	1.5	18	2	24
CP2T	380 V / 50 Hz	42 V / 200 Hz	1.8	25	2	23
CP3T	380 V / 50 Hz	42 V / 200 Hz	3.0	40	3	27
CM1M	220 V / 50 Hz	42 V / 200 Hz	0.8	11	1	21
CM2M	220 V / 50 Hz	42 V / 200 Hz	1.6	21	2	30
CM2T	380 V / 50 Hz	42 V / 200 Hz	1.8	25	2	30
CM3T	380 V / 50 Hz	42 V / 200 Hz	3.5	42	3	47
CM5T	380 V / 50 Hz	42 V / 200 Hz	5.0	65	3	55

Standard equipment: 2 metre cable

标准配置: 输入端2M电缆线

变频器与振动棒常用配置

COM PATIBILITY

CP1M CM1M			
CP2M CM2M	 		
CP2T CM2T	 		
CP3T CM3T	 	 	
CM5T	 	 	

NTE: The output current of Converters must be larger than the total current of needles, otherwise, this will cause damage of converters.

说明: 对于变频器拖动几根振动棒, 各振动棒电流之和必须小于变频器输出电流, 否则会造成变频器发热而烧坏。